

# C5

Compact full range point source for installation

## Features

- 6.5" bass reflex design combined with 1" dome tweeter
- Coaxial design
- Extended low frequency response at reduced power
- Integrated U-brackets for top and rear mounting
- 2x phoenix connectors on the back
- All Quint Audio loudspeakers are designed for use in combination with Quint Audio processors & amplifiers
- All Quint Audio loudspeaker presets are matched in level and phase at the crossover frequency for easy mix & match
- Factory system presets available

## Applications

- Stand alone full range loudspeaker

## Construction


- Birch plywood enclosure
- Durable hybrid coating, resistant to wear, impact, and weathering
- Klotz internal wiring
- Neutrik speakON® connectors
- Powder coated steel grilles with acoustically transparent fabric on the back



Model	C5
Filter	1-channel DSP control
Loudspeaker components	6.5"/1"
Impedance	8 Ohm
Peak SPL* / Freq. range (-6db)	124.5dB / 100Hz-20kHz
Max SPL* / Freq. range (-6db)	106.5dB / 100Hz-20kHz
Max SPL -10db / Freq. range (-6db)	96.5dB / 90Hz-20kHz
Max SPL -20db / Freq. range (-6db)	86.5dB / 45Hz-20kHz
Dispersion (HxV)	100° conical
Connections	2x
Weight	Phoenix 2,5/ 2-ST-5,08
Size (WxHxD)	5.5kg
	235 x 270 x 200mm

\* Measurements are conform to AES75 and carried out with P9 processor and A42 amplifier. Values are scaled to 1m free field.

## Accessories



C5-H1 (included)

